



Co-funded by the
Erasmus+ Programme
of the European Union





Remote Lab For Engineering Project
Erasmus+ Program


Raspberry Pi -Take Home Lab

Lab Experiment # 7

Raspberry Pi- Sensors




Tilt Sensor





- The tilt sensor is an instrument that is used for measuring the tilt in multiple axes of a reference plane.
- Tilt sensors measure the tilting position with reference to gravity and are used in numerous applications.
- They enable the easy detection of orientation or inclination. Similar to mercury switches, they may also be known as tilt switches or rolling ball sensors.




Tilt Sensor- Working Principle



- The tilt sensor has a metallic ball that is designed to move the two pins of the instrument from the 'on' to the 'off' position, and vice versa, if the sensor reaches a pre-determined angle.
- Tilt sensors are the environment-friendly version of a mercury-switch.




Tilt Sensor- Code



```
import RPi.GPIO as GPIO
import time
GPIO.setmode(GPIO.BCM)
GPIO.setup(18, GPIO.IN)
try:
    while True:
        i = GPIO.input(18)
        if i==1:
            print("Horizontal")
            time.sleep(0.1)
        elif i==0:
            print("Vertical")
            time.sleep(0.1)
except KeyboardInterrupt:
    GPIO.cleanup()
```

Tilt Sensor- Applications




- To monitor the angle at which a mobile phone or tablet is held for the auto-rotate function
- To detect the position of hand-held game systems and in game controllers
- To measure the angle at which a satellite antenna 'looks' toward a satellite
- To monitor laser levels and seismic activity.


Infrared Sensor





- This sensor comprises two main parts: IR-LED and Photo Diode.
- The IR-LED emits light of Infrared range 700 nanometers (nm) to 1 mm
- The Photo diode receives the light reflection off the detected object and changes its resistance
- The IR-sensor module outputs 'Signal' that carries the voltage according to variations in diode resistance.




IR color detection sensor



- The amount of reflected light depends on the color of the surface from which it is being reflected. Black is a perfect absorber and white is a perfect reflector.
- This sensor can be used in many applications, such as line follower, micro mouse, grid solver...



Infrared Sensor- Code & Connection



```
import RPi.GPIO as GPIO
import time
GPIO.setmode(GPIO.BCM)
GPIO.setup(18,GPIO.IN)
try:
    while True:
        i = GPIO.input(18)
        if i==0:
            print("No Interrupt")
            time.sleep(0.1)
        elif i==1:
            print("Interrupted")
            time.sleep(0.1)
except KeyboardInterrupt:
    GPIO.cleanup()
```

